Thread adapter installation for EXTEGRA IP 9000 FX series cameras

The following notice is an addendum to the Installation Manual (F01U304260) for EXTEGRA IP 9000 FX series cameras.



NOTICE!
These instructions provide supplemental information related to installation of the thread adapter supplied with the EXTEGRA IP 9000 FX series cameras.
Please read, follow, and retain the below information, in addition to following instructions in the Installation Manual before operating the camera.

Compatibility Information

This information applies to following Bosch camera models:

NXF-9130-A4 EXTEGRA IP starlight 9000 FX
NXF-9230-A4 EXTEGRA IP dynamic 9000 FX
NXF-9130-S4 EXTEGRA IP starlight 9000 FX
NXF-9230-S4 EXTEGRA IP dynamic 9000 FX

General

A ¾" NPT to M20 thread adapter is shipped with the camera. This addendum provides supplemental information for use and installation of the adapter to ensure a proper physical connection.

Installation Details

- As indicated in EXTEGRA installation instructions, follow manufacturer's instructions and apply a layer of *LA-CO Slic-Tite® Paste with PTFE* sealant (user-supplied) to the threads of the adapter.
- Ensure that thread adapter is securely tightened in the 3/4-in. NPT conduit opening.
- Do not use the thread adapter to interconnect directly to another enclosure.
- Do not install more than one thread adapter on a single entry port.
- Do not close off the adapter with a blanking plug.

Technical information for thread adapter

- Manufacturer: Hazardous Location Solutions, LLC
- Aluminum model number supplied with Aluminum housing EXTEGRA Camera: R1.3/4.20.N
- Stainless Steel model number supplied with Stainless Steel housing EXTEGRA Camera: R1.3/4.20.S
- Thread adapters are certified under certificates: SIRA 07ATEX1175X and IECEx SIR 07.0046X
- Flameproof joint information between the adapter and EXTEGRA Camera housing when installed: minimum 5 full threads engaged

Installation de l'adaptateur de filetage pour les caméras de la série EXTEGRA IP 9000 FX

La notice suivante est un supplément au manuel d'installation (F01U304260) pour les caméras de la série EXTEGRA IP 9000 FX.



Remarque!
Ces instructions fournissent des informations supplémentaires pour l'installation de l'adaptateur de filetage fourni avec les caméras de la série EXTEGRA IP 9000 FX.
Veuillez lire, respecter et retenir les informations ci-après, en complément des instructions fournies dans le manuel d'installation avant toute utilisation de la caméra.

Informations de compatibilité

Ces informations s'appliquent aux modèles suivants de caméras Bosch:

NXF-9130-A4 EXTEGRA IP starlight 9000 FX
NXF-9230-A4 EXTEGRA IP dynamic 9000 FX
NXF-9130-S4 EXTEGRA IP starlight 9000 FX
NXF-9230-S4 EXTEGRA IP dynamic 9000 FX

Généralités

Un adaptateur de filetage NPT vers M20 ¾" est livré avec la caméra. Le présent supplément offre des informations complémentaires pour l'utilisation et l'installation de l'adaptateur, pour garantir une connexion physique adéquate.

Instructions d’installation

- Comme indiqué dans les instructions d'installation EXTEGRA, suivez les instructions du fabricant et appliquez une couche de pâte d'étanchéité LA-CO Slic-Tite® avec polytétrafluoréthylène (non fournie) sur les filetages de l'adaptateur.
- Assurez-vous que l'adaptateur de filetage est fermement inséré dans le passage de câbles de 3/4".
- N'utilisez pas l'adaptateur de filetage pour réaliser directement une interconnexion vers un autre caisson.
- N'installez pas plus d'un adaptateur de filetage sur un port d'entrée.
- Ne fermez pas l'adaptateur avec un obturateur.

Informations techniques pour l'adaptateur de filetage

- Fabricant – Hazardous Location Solutions, LLC
- Numéro de modèle aluminium fourni avec le caisson en aluminium pour caméra EXTEGRA : R1.3/4.20.N
- Numéro de modèle en acier inoxydable fourni avec le caisson en acier inoxydable pour caméra EXTEGRA : R1.3/4.20.S
- Les adaptateurs de filetage sont certifiés conformes aux certificats : SIRA 07ATEX1175X and IECEx SIR 07.0046X
- Informations sur les joints antidéflagrants installés entre l'adaptateur et le caisson pour caméra EXTEGRA lorsqu'ils sont installés : au moins 5 tours de faits